


### S2000 Start Button



- Pin #1: Unused
- Pin #2: Parking Light Output
- Pin #3: Ground
- Pin #4: MASTERCELL Input
- Pin #5: Ground (or switched Ground)



- Pins are shown from the back of the switch with the writing on the button facing up.
- Carefully cut the copper trace on the printed circuit board with a sharp blade or a Dremmel tool. This is the second trace from the top as shown in the picture. The X indicates where to cut. Make sure that there is no electrical connection between the light bulb and pin number 4.
- Carefully scrape the green solder mask off of the copper in the two circled areas on the board as shown in the picture.
- Solder a 22-AWG jumper wire between the two exposed pads on the board. The red line shows the connection.

\*NOTE: Infitwire wire Colors & Connector Positions will vary for different kits. See the Configuration Sheet that came with your kit for exact wire colors and locations.

\*\*NOTE: MASTERCELL inputs must be ground switched. Applying 12-volts directly to an input will damage the MASTERCELL and void the warranty.

